

DCNM-PS2 Powering switch

DICENTIS



The Powering Switch is used in combination with an Audio Powering Switch to supply extra power to the DICENTIS network. The built-in Ethernet switch connects all devices in the system together in a network and supports loop-through connection, which makes it possible to connect the DICENTIS device to another DICENTIS device; even the last DICENTIS device in the loop can be connected to an (audio) powering switch to create cable redundancy. The powering switch has no user controls and can be fully controlled remotely.

Functions



Controls and Indicators

- Mains switch on the rear to power on the powering switch.
- Led on the front to show: green (power on), amber (standby), blinking (no connection to the system).
- Led on the rear to show: green (power availability on each powered socket), red (overload per powered socket).
- Ethernet led's yellow and amber for each socket.
- Independent powered sockets; a short circuit on one socket does no influence the other sockets.
- Supports hot plug and play.

- ▶ Zero network configuration
- ▶ Fully compatible to the Ethernet (IEEE802.3) and OMNEO standard
- ▶ Supports loop-through connection with cable redundancy
- ▶ Standby mode to be environment friendly

Interconnections

- Mains power supply auto ranging input.
- 1 socket with Ethernet without power, compatible with RJ45.
- 3 sockets with Ethernet with high power supply (144 W), compatible with RJ45.
- 1 socket with Ethernet with low power supply (15 W), compatible with RJ45.

Certifications and approvals

Region	Regulatory compliance/quality marks	
Europe	CE	DECL EC DCNM-PS2

Parts included

Quantity	Component
1	DCNM-PS2 DICENTIS Powering Switch

Technical specifications

Electrical

Supply voltage	100-240 Vac 50-60 Hz
Power consumption	530 W
System supply	48 Vdc
Total power supply	3x 144 W + 15 W

Mechanical

Mounting	Tabletop or mounted in a 19" rack
Dimensions (H x W x D)	
for tabletop use, with feet:	92 x 440 x 400 mm (3.6 x 17.3 x 15.7 in)
for 19" rack use, with brackets:	88 x 483 x 400 mm (3.5 x 19 x 15.7 in)
in front of brackets	40 mm (1.6 in)
behind brackets	360 mm (14.2 in)
Weight	7.4 kg (16.31 lbs)
Color	Traffic black RAL 9017 Pearl light grey RAL 9022

Environmental

Operating temperature	0 °C to +45 °C (-32 °F to +113 °F)
Storage and transport temperature	-20 °C to +70 °C (-4 °F to +158 °F)
Relative humidity	< 96 %, > 5 %

Ordering information**DCNM-PS2 Powering switch**

Switch for supplying additional power to the DICENTIS devices, built-in Ethernet switch.

DCNM-LSYS is required.

Order number **DCNM-PS2 | F.01U.308.937**

Services**EWE-DCNMPS-IW 12mths wrty ext DICENTIS powering switch**

12 months warranty extension

Order number **EWE-DCNMPS-IW | F.01U.348.759**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, LLC
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia